


0.02 to 8 GHz 19dBm Output Power Low Noise Amplifier with 15 dB Small Signal Gain

Our Product Introduction

Basic Information

- Place of Origin: CHINA
- Brand Name: ZR Hi-tech
- Model Number: LT-LA-000080-G15P19
- Minimum Order Quantity: 1
- Packaging Details: carton packing
- Delivery Time: 4 weeks
- Payment Terms: D/A,D/P,T/T



Product Specification

- Highlight: 8 GHz Low Noise Amplifier ,
19dBm Output Power Low Noise Amplifier

Product Description

0.02 to 8 GHz 19dBm Output Power Low Noise Amplifier with 15 dB Small Signal Gain

Quick Details

Aluminum Housing
Customizable Frequency
-40 ~+70 Operating Temperature
Small Signal Gain 15dB
CE, RoHS, REACH compliant
1 Year Warranty

Description

The LT-LA-000080-G15P19 from ZR is a RF Amplifier with Frequency 0.02 to 8 GHz, Small Signal Gain 15 dB, Gain Flatness ± 2.5 dB, Output Power 19dBm, Input Power 10 dBm. Tags: Power Amplifier.


Specifications

Electrical / Optical Characteristics (Ta=25 ± 3)

Items	Specification	Conditions
Part Number	LT-LA-000080-G15P19	
Configuration	Module with Connector	
Frequency Range	0.02 to 8 GHz	
Small Signal Gain	15 dB	
Gain Flatness	± 2.5 dB	
Output Power	19 dBm	
Input Power	10 dBm	
VSWR	2.0:1	
Power Supply	+12V / 100 mA	
Operating Temperature	-40 to +70	
Dimension	35x35x16 mm	

Note: for custom specs, please contact us directly.

Outline Drawing (Unit: mm)



ZRHITECH Sichuan ZR Hi-Tech Ltd.

☎ 17342580638 ✉ info@zrhitech.com 🌐 zrhitech.com

Room 507, Advanced Technology Achievement Western Transformation Center, No. 36 Xingke South Road,
Jinniu District, Chengdu, Sichuan, China