Adjustable Crystal Oscillator 125MHz Frequency Range For Flexibility

Basic Information

- Place of Origin:
- Brand Name:
- LT-CR-O-125M-5032 Model Number:


CHINA

1

ZR Hi-Tech

4 weeks T/T

- Minimum Order Quantity:
- Packaging Details: carton packing
- Delivery Time:
- Payment Terms:



LT-CR-0-125M-5032

Product Specification

- Features:
- Low Power Consumption
- Product Name: LT-CR Series Crystal Oscillator
- Application:
- Material:
- Temperature:
- Frequency Range:
- Color:
- Highlight:

Instruments In The Field Of National Defense Aluminum

crystal oscillator 125MHz

Various Electronic Equipment And

- -40~85°C
- Operating Voltage:
- ±30ppm 2.97~3.63V Silver 125 mhz oscillator, adjustable crystal oscillator,

Our Product Introduction

125MHz LT-CR series crystal oscillator

Quick Detail:

· Aluminum housing · Broadband Frquency · -40°C~+85°C operating temperature · SMD package · High precision · Low phase noise · CMOS Output Waveform · CE, RoHS, REACH compliant · 1 Year Warranty

Description:


The LT-CR-O-125M-5032 is the newest addition to ZR's line of Crystal Oscillator (XO) with a HCMOS output from 1 to 125 MHz. This XO requires a supply voltage of 2.97V to 3.63V and consumes 60 mA of current. They are available in a hermetically sealed surface-mount package and measure5x3.2x1.3mm. These XOs are widely used in various electronic equipment and instruments in the field of national defense.


Specifications:

Electrical / Optical Characteristics (Ta=25°C±3°C)

Items	Specification		Conditions
Part Number	LT-CR-O-125M-5032		
Frequency Range	125MHz		
Operating Voltage	2.97~3.63V		
Frequency Stability vs. Temperature	±30ppm		@-40~85°C
Output Waveform	HCMOS		
Output Load	15pF		
Duty Cycle(%)	40~60		
Rise/Fall Time(ns)	6ns	10%~90%	-0.1Vdd→0.9Vdd
Current Consumption(mA)	60		3.3V non-loaded
Dimension	5x3.2x1.3mm		
Note: for custom specs, plea	se contact us di	rectly.	

Outline Drawing (Unit: mm):





PIN	FUNCTION	
1	OE	
2	Ground	
3	Output	
4	Vdd	

13541202623

⋛ЗЁТКНІТЕСН Sichuan ZR Hi-Tech Ltd.



No.1411, Zhuye Building, 100 Xingping Road, Jinniu District, Chengdu, Sichuan Province, CHINA