6 to 18 GHz 20 Watt LT-PD Series 16-Way Power Divider

Basic Information

• Place of Origin:

Brand Name: ZR Hi-tech

zrhitech.com

Model Number: LT-PD-16S-060180

CHINA

4 weeks

D/A,D/P,T/T

1

Sichuan ZR Hi-Tech Ltd.

- Minimum Order Quantity:
- Packaging Details: carton packing
- Delivery Time:
- Payment Terms:





LT-PD-16S-060180

Product Specification

• Highlight:

6 to 18 GHz Power Divider

Our Product Introduction

Product Description

6 to 18 GHz 16-Way Power Divider

Quick Detail:

- ·16-Way Power Divider
- · Stripline Design
- -55°C~+85°C operating temperature
- · 6 to 18 GHz Frequency Range
- · Max Power 20 Watt
- · Insertion Loss < 2.8 dB
- · Isolation > 17 dB
- · CE, RoHS, REACH compliant
- · 1 Year Warranty

Description:


The LT-PD-16S-060180 from ZR is a 16-way power divider that operates from 6 to 18 GHz and can handle up to 20 Watt (CW) with 2.8 dB max insertion loss and 17 dB min isolation, The package interface uses SMA-Female connectors and is REACH and RoHS compliant. More details for LT-PD-16S-060180 can be seen below.

Specifications:

Electrical / Optical Characteristics (Ta=25°C±3°C)

Items	Specification	Conditions
Part Number	LT-PD-16S-060180	
Frequency Range	6 to 18 GHz	
Impedance	50 Ohms	
Input VSWR	1.6:1 Max.	
Output VSWR	1.5:1 Max.	
Insertion Loss	2.8 dB Max.	Excluding Nominal Splitter
		Loss 3.0dB
Isolation	17 dB Min.	
Amplitude Balance	0.8 dB Max.	
Phase Balance	10 Degrees Max.	
Input Power	20 kW	
Connectors	SMA-Female	
Dimension	49.8x222.8x12.7 mm	
Note: for custom spec	s, please contact us directly	•

Outline Drawing (Unit: mm):



Жіткесн Sichuan ZR Hi-Tech Ltd.

- 13541202623
 - info@zrhitech.com C zrhitech.com