2 to 18 GHz 20 Watts LT-DC Series 16dB Directional Coupler

Basic Information

Place of Origin: CHINA
 Brand Name: ZR Hi-Tech
 Model Number: LT-DC16-020180S

Minimum Order Quantity: 1

Packaging Details: carton packing
Delivery Time: 4 weeks
Payment Terms: T/T,D/A,D/P



Product Specification

Product Description

2 to 18 GHz 16dB Directional Coupler

Quick Detail:

- · 16dB Directional Coupler
- · Directivity > 16 dB
- · 2 to 18 GHz Frequency Range
- · Lost VSWR < 1.4:1
- · Coupling 16±0.5 dB
- · Max Power 20 Watts(CW)
- · CE, RoHS, REACH compliant
- · 1 Year Warranty

Description:


The LT-DC16-020180S from ZR is a 16dB Directional Coupler that operates from 2 to 18 GHz and can handle up to 20 Watt (CW) with 16 dB directivity min and 1.4:1 VSWR max, The package interface uses SMA Female connectors and is REACH and RoHS compliant. More details for LT-DC16-020180S can be seen below.

Specifications:

Electrical / Optical Characteristics (Ta=25°C±3°C)

Items	Specification	Conditions
Part Number	LT-DC16-020180S	
Frequency Range	2 to 18 GHz	
Coupling	16±0.5 dB	
Impedance	50 Ohms	
Main Line VSWR	1.4:1 Max.	
Coupling VSWR	1.4:1 Max.	
Insertion Loss	0.8 dB Max.	
Frequency Balance	1.0 dB Max.	
Directivity	16 dB Min.	
Input Power	20 W	
Connectors	SMA Female	
Weight	55 g	
Dimension	57.2x17.8x12.7 mm	
Note: for custom specs, please contact us directly.		

Outline Drawing (Unit: mm):



ZRHITECH Sichuan ZR Hi-Tech Ltd.



13541202623



info@zrhitech.com



Zrhitech.com